

Enclosed Alphanumeric Supplement

Range: 1F100–1F1FF

The Unicode Standard, Version 15.1

This file contains an excerpt from the character code tables and list of character names for *The Unicode Standard, Version 15.1*

This file may be changed at any time without notice to reflect errata, or other updates to the Unicode Standard. See <https://www.unicode.org/errata/> for an up-to-date list of errata.

See <https://www.unicode.org/charts/> for access to a complete list of the latest character code charts. See <https://www.unicode.org/charts/PDF/Unicode-15.1/> for charts showing only the characters added in Unicode 15.1. See <https://www.unicode.org/Public/15.1.0/charts/> for a complete archived file of character code charts for Unicode 15.1. See <https://www.unicode.org/charts/About.html#Conventions> for conventions used in these code charts, and other general information.

Disclaimer

These charts are provided as the online reference to the character contents of the Unicode Standard, Version 15.1 but do not provide all the information needed to fully support individual scripts using the Unicode Standard. For a complete understanding of the use of the characters contained in this file, please consult the appropriate sections of The Unicode Standard, Version 15.1, online at <https://www.unicode.org/versions/Unicode15.1.0/>, as well as Unicode Standard Annexes #9, #11, #14, #15, #24, #29, #31, #34, #38, #41, #42, #44, #45, and #50, the other Unicode Technical Reports and Standards, and the Unicode Character Database, which are available online.

See <https://www.unicode.org/ucd/> and <http://www.unicode.org/reports/>

A thorough understanding of the information contained in these additional sources is required for a successful implementation.

Copying characters from the character code tables or list of character names is not recommended, because for production reasons the PDF files for the code charts cannot guarantee that the correct character codes will always be copied.

Fonts

The shapes of the reference glyphs used in these code charts are not prescriptive. Considerable variation is to be expected in actual fonts. The particular fonts used in these charts were provided to the Unicode Consortium by a number of different font designers, who own the rights to the fonts.

See <https://www.unicode.org/charts/fonts.html> for a list.

Terms of Use

You may freely use these code charts for personal or internal business uses only. You may not incorporate them either wholly or in part into any product or publication, or otherwise distribute them without express written permission from the Unicode Consortium. However, you may provide links to these charts.

The fonts and font data used in production of these code charts may NOT be extracted, or used in any other way in any product or publication, without permission or license granted by the typeface owner(s).

The Unicode Consortium is not liable for errors or omissions in this file or the standard itself. Information on characters added to the Unicode Standard since the publication of the most recent version of the Unicode Standard, as well as on characters currently being considered for addition to the Unicode Standard can be found on the Unicode web site.

See <https://www.unicode.org/pending/pending.html> and <http://www.unicode.org/alloc/Pipeline.html>.

See <https://www.unicode.org/charts/About.html> for more information concerning the conventions and symbols used in these code charts.

Copyright © 1991–2023 Unicode, Inc. All rights reserved. See <https://www.unicode.org/copyright.html>

	1F10	1F11	1F12	1F13	1F14	1F15	1F16	1F17	1F18	1F19	1F1A	1F1B	1F1C	1F1D	1F1E	1F1F
0	0. 1F100	(A) 1F110	(Q) 1F120	A 1F130	Q 1F140	ⓐ 1F150	ⓑ 1F160	Ⓐ 1F170	Ⓚ 1F180	DJ 1F190	5.1 1F1A0					K 1F1F0
1	0, 1F101	(B) 1F111	(R) 1F121	B 1F131	R 1F141	ⓐ 1F151	ⓑ 1F161	Ⓑ 1F171	Ⓚ 1F181	CL 1F191	7.1 1F1A1					L 1F1F1
2	1, 1F102	(C) 1F112	(S) 1F122	C 1F132	S 1F142	ⓐ 1F152	ⓑ 1F162	Ⓒ 1F172	Ⓚ 1F182	COOL 1F192	22.2 1F1A2					M 1F1F2
3	2, 1F103	(D) 1F113	(T) 1F123	D 1F133	T 1F143	ⓐ 1F153	ⓑ 1F163	Ⓓ 1F173	Ⓚ 1F183	FREE 1F193	60P 1F1A3					N 1F1F3
4	3, 1F104	(E) 1F114	(U) 1F124	E 1F134	U 1F144	ⓐ 1F154	ⓑ 1F164	Ⓔ 1F174	Ⓚ 1F184	ID 1F194	120P 1F1A4					O 1F1F4
5	4, 1F105	(F) 1F115	(V) 1F125	F 1F135	V 1F145	ⓐ 1F155	ⓑ 1F165	Ⓕ 1F175	Ⓚ 1F185	NEW 1F195	d 1F1A5					P 1F1F5
6	5, 1F106	(G) 1F116	(W) 1F126	G 1F136	W 1F146	ⓐ 1F156	ⓑ 1F166	Ⓖ 1F176	Ⓚ 1F186	NG 1F196	HC 1F1A6				A 1F1E6	Q 1F1F6
7	6, 1F107	(H) 1F117	(X) 1F127	H 1F137	X 1F147	ⓐ 1F157	ⓑ 1F167	Ⓗ 1F177	Ⓚ 1F187	OK 1F197	HDR 1F1A7				B 1F1E7	R 1F1F7
8	7, 1F108	(I) 1F118	(Y) 1F128	I 1F138	Y 1F148	ⓐ 1F158	ⓑ 1F168	Ⓘ 1F178	Ⓚ 1F188	SOS 1F198	Hi-Res 1F1A8				C 1F1E8	S 1F1F8
9	8, 1F109	(J) 1F119	(Z) 1F129	J 1F139	Z 1F149	ⓐ 1F159	ⓑ 1F169	Ⓙ 1F179	Ⓚ 1F189	UP! 1F199	Loss less 1F1A9				D 1F1E9	T 1F1F9
A	9, 1F10A	(K) 1F11A	(S) 1F12A	K 1F13A	HV 1F14A	ⓐ 1F15A	MC 1F16A	Ⓚ 1F17A	Ⓚ 1F18A	VS 1F19A	SHV 1F1AA				E 1F1EA	U 1F1FA
B	Ⓚ 1F10B	(L) 1F11B	(C) 1F12B	L 1F13B	MV 1F14B	ⓐ 1F15B	MD 1F16B	Ⓚ 1F17B	Ⓚ 1F18B	3D 1F19B	UHD 1F1AB				F 1F1EB	V 1F1FB
C	Ⓚ 1F10C	(M) 1F11C	(R) 1F12C	M 1F13C	SD 1F14C	ⓐ 1F15C	MR 1F16C	Ⓚ 1F17C	Ⓚ 1F18C	2nd Scr 1F19C	VOD 1F1AC				G 1F1EC	W 1F1FC
D	Ⓚ 1F10D	(N) 1F11D	(CD) 1F12D	N 1F13D	SS 1F14D	ⓐ 1F15D	Ⓚ 1F16D	Ⓚ 1F17D	Ⓚ 1F18D	2K 1F19D	Ⓚ 1F1AD				H 1F1ED	X 1F1FD
E	Ⓚ 1F10E	(O) 1F11E	(Wz) 1F12E	O 1F13E	PPV 1F14E	ⓐ 1F15E	Ⓚ 1F16E	Ⓚ 1F17E	Ⓚ 1F18E	4K 1F19E					I 1F1EE	Y 1F1FE
F	Ⓚ 1F10F	(P) 1F11F	Ⓚ 1F12F	P 1F13F	WC 1F14F	ⓐ 1F15F	Ⓚ 1F16F	Ⓚ 1F17F	Ⓚ 1F18F	8K 1F19F					J 1F1EF	Z 1F1FF

Number with full stop

This symbol completes the set of numbers with full stop starting at 2488.

1F100 0. DIGIT ZERO FULL STOP
≈ 0030 0 002E .

Numbers with comma

1F101 0, DIGIT ZERO COMMA
≈ 0030 0 002C ,

1F102 1, DIGIT ONE COMMA
≈ 0031 1 002C ,

1F103 2, DIGIT TWO COMMA
≈ 0032 2 002C ,

1F104 3, DIGIT THREE COMMA
≈ 0033 3 002C ,

1F105 4, DIGIT FOUR COMMA
≈ 0034 4 002C ,

1F106 5, DIGIT FIVE COMMA
≈ 0035 5 002C ,

1F107 6, DIGIT SIX COMMA
≈ 0036 6 002C ,

1F108 7, DIGIT SEVEN COMMA
≈ 0037 7 002C ,

1F109 8, DIGIT EIGHT COMMA
≈ 0038 8 002C ,

1F10A 9, DIGIT NINE COMMA
≈ 0039 9 002C ,

Circled sans-serif digits

These digits complement the sans-serif digit sets in the Dingbat block ranges 2780-2789 and 278A-2793.

1F10B ① DINGBAT CIRCLED SANS-SERIF DIGIT ZERO

1F10C ② DINGBAT NEGATIVE CIRCLED SANS-SERIF DIGIT ZERO

Creative Commons symbols

Part of a Creative Commons symbol set also including 229C, 1F16D, 1F16E, and 1F16F.

1F10D ④ CIRCLED ZERO WITH SLASH
= no rights reserved

1F10E ⑤ CIRCLED ANTICLOCKWISE ARROW
= share alike

1F10F ⑥ CIRCLED DOLLAR SIGN WITH OVERLAID BACKSLASH
= non commercial

Parenthesized Latin letters

This set provides uppercase versions of the set starting at 249C. Parenthesized Latin letters do not have case mappings.

1F110 (A) PARENTHESIZED LATIN CAPITAL LETTER A
≈ 0028 (0041 A 0029)

1F111 (B) PARENTHESIZED LATIN CAPITAL LETTER B
≈ 0028 (0042 B 0029)

1F112 (C) PARENTHESIZED LATIN CAPITAL LETTER C
≈ 0028 (0043 C 0029)

1F113 (D) PARENTHESIZED LATIN CAPITAL LETTER D
≈ 0028 (0044 D 0029)

1F114 (E) PARENTHESIZED LATIN CAPITAL LETTER E
≈ 0028 (0045 E 0029)

1F115 (F) PARENTHESIZED LATIN CAPITAL LETTER F
≈ 0028 (0046 F 0029)

1F116 (G) PARENTHESIZED LATIN CAPITAL LETTER G
≈ 0028 (0047 G 0029)

1F117 (H) PARENTHESIZED LATIN CAPITAL LETTER H
≈ 0028 (0048 H 0029)

1F118 (I) PARENTHESIZED LATIN CAPITAL LETTER I
≈ 0028 (0049 I 0029)

1F119 (J) PARENTHESIZED LATIN CAPITAL LETTER J
≈ 0028 (004A J 0029)

1F11A (K) PARENTHESIZED LATIN CAPITAL LETTER K
≈ 0028 (004B K 0029)

1F11B (L) PARENTHESIZED LATIN CAPITAL LETTER L
≈ 0028 (004C L 0029)

1F11C (M) PARENTHESIZED LATIN CAPITAL LETTER M
≈ 0028 (004D M 0029)

1F11D (N) PARENTHESIZED LATIN CAPITAL LETTER N
≈ 0028 (004E N 0029)

1F11E (O) PARENTHESIZED LATIN CAPITAL LETTER O
≈ 0028 (004F O 0029)

1F11F (P) PARENTHESIZED LATIN CAPITAL LETTER P
≈ 0028 (0050 P 0029)

1F120 (Q) PARENTHESIZED LATIN CAPITAL LETTER Q
≈ 0028 (0051 Q 0029)

1F121 (R) PARENTHESIZED LATIN CAPITAL LETTER R
≈ 0028 (0052 R 0029)

1F122 (S) PARENTHESIZED LATIN CAPITAL LETTER S
≈ 0028 (0053 S 0029)

1F123 (T) PARENTHESIZED LATIN CAPITAL LETTER T
≈ 0028 (0054 T 0029)

1F124 (U) PARENTHESIZED LATIN CAPITAL LETTER U
≈ 0028 (0055 U 0029)

1F125 (V) PARENTHESIZED LATIN CAPITAL LETTER V
≈ 0028 (0056 V 0029)

1F126 (W) PARENTHESIZED LATIN CAPITAL LETTER W
≈ 0028 (0057 W 0029)

1F127 (X) PARENTHESIZED LATIN CAPITAL LETTER X
≈ 0028 (0058 X 0029)

1F128 (Y) PARENTHESIZED LATIN CAPITAL LETTER Y
≈ 0028 (0059 Y 0029)

1F129 (Z) PARENTHESIZED LATIN CAPITAL LETTER Z
≈ 0028 (005A Z 0029)

Latin letter with tortoise shell brackets

1F12A [S] TORTOISE SHELL BRACKETED LATIN CAPITAL LETTER S
• used in baseball scoring
≈ 3014 [0053 S 3015]

Circled italic Latin letters

1F12B © CIRCLED ITALIC LATIN CAPITAL LETTER C
= compact disc, single disc record
≈ <circle> 0043 C

1F12C ® CIRCLED ITALIC LATIN CAPITAL LETTER R
= disc record
≈ <circle> 0052 R

Circled Latin letters or letter sequences

1F12D © CIRCLED CD
→ 33C5 cd square cd
≈ <circle> 0043 C 0044 D

1F12E ™ CIRCLED WZ
• from the German term “Warenzeichen”
• indicate a trademarked term without making a legal claim of trademark status
• decomposition is anomalous, as the usual glyph shows a capital W and a small z
→ 2122 ™ trade mark sign
≈ <circle> 0057 W 005A Z

- 1F12F © COPYLEFT SYMBOL
 → 00A9 © copyright sign
 → 2183 ㊀ roman numeral reversed one hundred




Squared Latin letters

- 1F130 A SQUARED LATIN CAPITAL LETTER A
 = Anreisetag (day of arrival)
 ≈ <square> 0041 A
- 1F131 B SQUARED LATIN CAPITAL LETTER B
 = bank
 = b-mode stereo compression broadcasting service (ARIB STD B24)
 ≈ <square> 0042 B
- 1F132 C SQUARED LATIN CAPITAL LETTER C
 ≈ <square> 0043 C
- 1F133 D SQUARED LATIN CAPITAL LETTER D
 ≈ <square> 0044 D
- 1F134 E SQUARED LATIN CAPITAL LETTER E
 ≈ <square> 0045 E
- 1F135 F SQUARED LATIN CAPITAL LETTER F
 ≈ <square> 0046 F
- 1F136 G SQUARED LATIN CAPITAL LETTER G
 ≈ <square> 0047 G
- 1F137 H SQUARED LATIN CAPITAL LETTER H
 ≈ <square> 0048 H
- 1F138 I SQUARED LATIN CAPITAL LETTER I
 ≈ <square> 0049 I
- 1F139 J SQUARED LATIN CAPITAL LETTER J
 ≈ <square> 004A J
- 1F13A K SQUARED LATIN CAPITAL LETTER K
 ≈ <square> 004B K
- 1F13B L SQUARED LATIN CAPITAL LETTER L
 ≈ <square> 004C L
- 1F13C M SQUARED LATIN CAPITAL LETTER M
 ≈ <square> 004D M
- 1F13D N SQUARED LATIN CAPITAL LETTER N
 = news (ARIB STD B24)
 ≈ <square> 004E N
- 1F13E O SQUARED LATIN CAPITAL LETTER O
 ≈ <square> 004F O
- 1F13F P SQUARED LATIN CAPITAL LETTER P
 = progressive broadcasting (ARIB STD B24)
 ≈ <square> 0050 P
- 1F140 Q SQUARED LATIN CAPITAL LETTER Q
 ≈ <square> 0051 Q
- 1F141 R SQUARED LATIN CAPITAL LETTER R
 ≈ <square> 0052 R
- 1F142 S SQUARED LATIN CAPITAL LETTER S
 = stereo broadcasting service (ARIB STD B24)
 ≈ <square> 0053 S
- 1F143 T SQUARED LATIN CAPITAL LETTER T
 = tobacconist
 ≈ <square> 0054 T
- 1F144 U SQUARED LATIN CAPITAL LETTER U
 ≈ <square> 0055 U
- 1F145 V SQUARED LATIN CAPITAL LETTER V
 ≈ <square> 0056 V
- 1F146 W SQUARED LATIN CAPITAL LETTER W
 = wide-format 16:9 broadcasting service (ARIB STD B24)
 ≈ <square> 0057 W
- 1F147 X SQUARED LATIN CAPITAL LETTER X
 ≈ <square> 0058 X




- 1F148 Y SQUARED LATIN CAPITAL LETTER Y
 ≈ <square> 0059 Y
- 1F149 Z SQUARED LATIN CAPITAL LETTER Z
 ≈ <square> 005A Z
- 1F14A HV SQUARED HV
 = hdtv
 ≈ <square> 0048 H 0056 V
- 1F14B MV SQUARED MV
 = multi-view television
 ≈ <square> 004D M 0056 V
- 1F14C SD SQUARED SD
 = sdtv
 ≈ <square> 0053 S 0044 D
- 1F14D SS SQUARED SS
 = surround stereo broadcasting service
 ≈ <square> 0053 S 0053 S
- 1F14E PPV SQUARED PPV
 = pay-per-view
 ≈ <square> 0050 P 0050 P 0056 V
- 1F14F WC SQUARED WC
 = water closet, public toilet
 → 1F6BE 🚻 water closet
 ≈ <square> 0057 W 0043 C

White on black circled Latin letters





- 1F150 A NEGATIVE CIRCLED LATIN CAPITAL LETTER A
 = airport
- 1F151 B NEGATIVE CIRCLED LATIN CAPITAL LETTER B
- 1F152 C NEGATIVE CIRCLED LATIN CAPITAL LETTER C
- 1F153 D NEGATIVE CIRCLED LATIN CAPITAL LETTER D
- 1F154 E NEGATIVE CIRCLED LATIN CAPITAL LETTER E
- 1F155 F NEGATIVE CIRCLED LATIN CAPITAL LETTER F
 = ferry
- 1F156 G NEGATIVE CIRCLED LATIN CAPITAL LETTER G
- 1F157 H NEGATIVE CIRCLED LATIN CAPITAL LETTER H
 = hotel (ARIB STD B24)
- 1F158 I NEGATIVE CIRCLED LATIN CAPITAL LETTER I
- 1F159 J NEGATIVE CIRCLED LATIN CAPITAL LETTER J
- 1F15A K NEGATIVE CIRCLED LATIN CAPITAL LETTER K
 = Kurort (spa)
 → 2668 ♨️ hot springs
- 1F15B L NEGATIVE CIRCLED LATIN CAPITAL LETTER L
 = light rail
 → 1F688 🚊 light rail
- 1F15C M NEGATIVE CIRCLED LATIN CAPITAL LETTER M
 = metro
 → 1F687 🚇 metro
- 1F15D N NEGATIVE CIRCLED LATIN CAPITAL LETTER N
- 1F15E O NEGATIVE CIRCLED LATIN CAPITAL LETTER O
- 1F15F P NEGATIVE CIRCLED LATIN CAPITAL LETTER P
 = parking space (ARIB STD B24)
- 1F160 Q NEGATIVE CIRCLED LATIN CAPITAL LETTER Q
- 1F161 R NEGATIVE CIRCLED LATIN CAPITAL LETTER R
 = Raststätte (rest stop)
- 1F162 S NEGATIVE CIRCLED LATIN CAPITAL LETTER S
 = Stadtbahn (metropolitan railway)
- 1F163 T NEGATIVE CIRCLED LATIN CAPITAL LETTER T
 = Tankstelle (petrol station)
 → 26FD 🛢️ fuel pump
- 1F164 U NEGATIVE CIRCLED LATIN CAPITAL LETTER U
 = underground rail
 → 1F687 🚇 metro
- 1F165 V NEGATIVE CIRCLED LATIN CAPITAL LETTER V
- 1F166 W NEGATIVE CIRCLED LATIN CAPITAL LETTER W

- 1F167  NEGATIVE CIRCLED LATIN CAPITAL LETTER X
 1F168  NEGATIVE CIRCLED LATIN CAPITAL LETTER Y
 1F169  NEGATIVE CIRCLED LATIN CAPITAL LETTER Z

Raised squared Latin sequences






















- 1F16A  RAISED MC SIGN
 = marque de commerce
 • used in Canada
 → 2122 TM trade mark sign
 ≈ <sup> 004D **M** 0043 **C**
- 1F16B  RAISED MD SIGN
 = marque déposée
 • used in Canada
 → 00AE [®] registered sign
 ≈ <sup> 004D **M** 0044 **D**
- 1F16C  RAISED MR SIGN
 = marca registrada
 • used primarily in Spanish and Portuguese speaking communities to indicate a registered trademark
 → 00AE [®] registered sign
 ≈ <sup> 004D **M** 0052 **R**














Creative Commons symbols

- 1F16D  CIRCLED CC
 = Creative Commons license
 → 229C 
- 1F16E  CIRCLED C WITH OVERLAID BACKSLASH
 = public domain
- 1F16F  CIRCLED HUMAN FIGURE
 = attribution, credit












White on black squared Latin letters

The square edges may be slightly rounded.













- 1F170  NEGATIVE SQUARED LATIN CAPITAL LETTER A
 = blood type A
- 1F171  NEGATIVE SQUARED LATIN CAPITAL LETTER B
 = blood type B
- 1F172  NEGATIVE SQUARED LATIN CAPITAL LETTER C
 = centre, city centre
- 1F173  NEGATIVE SQUARED LATIN CAPITAL LETTER D
- 1F174  NEGATIVE SQUARED LATIN CAPITAL LETTER E
- 1F175  NEGATIVE SQUARED LATIN CAPITAL LETTER F
 = Feuerwache (fire department)
- 1F176  NEGATIVE SQUARED LATIN CAPITAL LETTER G
- 1F177  NEGATIVE SQUARED LATIN CAPITAL LETTER H
 = Haltestelle (bus stop)
 → 1F68F  bus stop
- 1F178  NEGATIVE SQUARED LATIN CAPITAL LETTER I
- 1F179  NEGATIVE SQUARED LATIN CAPITAL LETTER J
 = junction (ARIB STD B24)
- 1F17A  NEGATIVE SQUARED LATIN CAPITAL LETTER K
- 1F17B  NEGATIVE SQUARED LATIN CAPITAL LETTER L
 = leisure center (ARIB STD B24)
- 1F17C  NEGATIVE SQUARED LATIN CAPITAL LETTER M
 = museum, cultural center (ARIB STD B24)
- 1F17D  NEGATIVE SQUARED LATIN CAPITAL LETTER N
- 1F17E  NEGATIVE SQUARED LATIN CAPITAL LETTER O
 = blood type O
- 1F17F  NEGATIVE SQUARED LATIN CAPITAL LETTER P
 = parking space empty-full (ARIB STD B24)
- 1F180  NEGATIVE SQUARED LATIN CAPITAL LETTER Q
- 1F181  NEGATIVE SQUARED LATIN CAPITAL LETTER R
- 1F182  NEGATIVE SQUARED LATIN CAPITAL LETTER S
- 1F183  NEGATIVE SQUARED LATIN CAPITAL LETTER T







- 1F184  NEGATIVE SQUARED LATIN CAPITAL LETTER U
- 1F185  NEGATIVE SQUARED LATIN CAPITAL LETTER V
- 1F186  NEGATIVE SQUARED LATIN CAPITAL LETTER W
- 1F187  NEGATIVE SQUARED LATIN CAPITAL LETTER X
- 1F188  NEGATIVE SQUARED LATIN CAPITAL LETTER Y
- 1F189  NEGATIVE SQUARED LATIN CAPITAL LETTER Z
- 1F18A  CROSSED NEGATIVE SQUARED LATIN CAPITAL LETTER P
 = parking space closed
- 1F18B  NEGATIVE SQUARED IC
 = interchange, ramp
- 1F18C  NEGATIVE SQUARED PA
 = parking area
- 1F18D  NEGATIVE SQUARED SA
 = service area
- 1F18E  NEGATIVE SQUARED AB
 = blood type AB
- 1F18F  NEGATIVE SQUARED WC
 = water closet, public toilet
 → 1F6BE  water closet

Squared Latin letter sequences



- 1F190  SQUARE DJ
 = disc jockey
 ≈ <square> 0044 **D** 004A **J**
- 1F191  SQUARED CL
 = clear
- 1F192  SQUARED COOL
- 1F193  SQUARED FREE
 = free postage
- 1F194  SQUARED ID
 = identification, ID
- 1F195  SQUARED NEW
- 1F196  SQUARED NG
 = no good
- 1F197  SQUARED OK
- 1F198  SQUARED SOS
 = search, hunt for missing person
- 1F199  SQUARED UP WITH EXCLAMATION MARK
 = new information, update
- 1F19A  SQUARED VS
 = versus

Squared Latin letter sequences from ARIB STD B62

- 1F19B  SQUARED THREE D
- 1F19C  SQUARED SECOND SCREEN
- 1F19D  SQUARED TWO K
- 1F19E  SQUARED FOUR K
- 1F19F  SQUARED EIGHT K
- 1F1A0  SQUARED FIVE POINT ONE
 • denotes 5.1-channel surround sound
- 1F1A1  SQUARED SEVEN POINT ONE
 • denotes 7.1-channel surround sound
- 1F1A2  SQUARED TWENTY-TWO POINT TWO
 • denotes 22.2-channel surround sound
- 1F1A3  SQUARED SIXTY P
 • denotes 60Hz frame rate with progressive scanning
- 1F1A4  SQUARED ONE HUNDRED TWENTY P
 • denotes 120Hz frame rate with progressive scanning
- 1F1A5  SQUARED LATIN SMALL LETTER D
 = data
- 1F1A6  SQUARED HC
 = hybrid cast



























1F1A7		SQUARED HDR = high dynamic range
1F1A8		SQUARED HI-RES = high resolution
1F1A9		SQUARED LOSSLESS
1F1AA		SQUARED SHV = super high vision
1F1AB		SQUARED UHD = ultra-high definition
1F1AC		SQUARED VOD = video on demand

Miscellaneous symbol

1F1AD		MASK WORK SYMBOL <ul style="list-style-type: none"> • indicates intellectual property protection for integrated circuit layouts → 00A9 © copyright sign → 24C2  circled latin capital letter m
-------	---	--

Regional indicator symbols

These characters can be used in pairs to represent regional codes. In some emoji implementations, certain pairs may be recognized and displayed by alternate means; for instance, an implementation might recognize F + R and display this combination with a symbol representing the flag of France.

1F1E6		REGIONAL INDICATOR SYMBOL LETTER A
1F1E7		REGIONAL INDICATOR SYMBOL LETTER B
1F1E8		REGIONAL INDICATOR SYMBOL LETTER C
1F1E9		REGIONAL INDICATOR SYMBOL LETTER D
1F1EA		REGIONAL INDICATOR SYMBOL LETTER E
1F1EB		REGIONAL INDICATOR SYMBOL LETTER F
1F1EC		REGIONAL INDICATOR SYMBOL LETTER G
1F1ED		REGIONAL INDICATOR SYMBOL LETTER H
1F1EE		REGIONAL INDICATOR SYMBOL LETTER I
1F1EF		REGIONAL INDICATOR SYMBOL LETTER J
1F1F0		REGIONAL INDICATOR SYMBOL LETTER K
1F1F1		REGIONAL INDICATOR SYMBOL LETTER L
1F1F2		REGIONAL INDICATOR SYMBOL LETTER M
1F1F3		REGIONAL INDICATOR SYMBOL LETTER N
1F1F4		REGIONAL INDICATOR SYMBOL LETTER O
1F1F5		REGIONAL INDICATOR SYMBOL LETTER P
1F1F6		REGIONAL INDICATOR SYMBOL LETTER Q
1F1F7		REGIONAL INDICATOR SYMBOL LETTER R
1F1F8		REGIONAL INDICATOR SYMBOL LETTER S
1F1F9		REGIONAL INDICATOR SYMBOL LETTER T
1F1FA		REGIONAL INDICATOR SYMBOL LETTER U
1F1FB		REGIONAL INDICATOR SYMBOL LETTER V
1F1FC		REGIONAL INDICATOR SYMBOL LETTER W
1F1FD		REGIONAL INDICATOR SYMBOL LETTER X
1F1FE		REGIONAL INDICATOR SYMBOL LETTER Y
1F1FF		REGIONAL INDICATOR SYMBOL LETTER Z